




L0-280024-8xx-Cxxxx-K118



INTRODUCTION

LED module is an advanced light source designed for the best energy efficient and eco-friendly indoor lighting. It is based on medium power LEDs produced by the leader of the LED technology OSRAM. Using newest technology we provide the best solution for lighting. With a very high value of CRI and simple installation. Connecting few LED modules allows to create complex lighting. Optional push terminals provide quick installation of the entire lighting system. This solution is the best for indoor ceiling-mounted and wall-mounted luminaries.

LED Type	OSRAM E2 - GW JBLMS1.EM
LED Quantity	24 pcs
Dimension	280x24 mm
Power Supply Type	Constant Current (CC)
Input Current	max. 200, 300, 400, 600, 1200 mA depending on version
Viewing Angle	150°
Material Thickness	1,5 mm
Cable Connection	ADELS 351102
Max Ambient Temperature	45°C
CRI	>80

FEATURES

LEDs have significant advantages compared to other types of lighting and are easy to use. LEDs are versatile and virtually maintenance free.

- Efficiency of the module up to 148 lm/W
- Rigid board LED module
- Viewing angle at 50% I_v: 120°
- High colour rendering index CRI >80
- Modules need heat-sink when T_c point exceeds 70°C
- Small colour tolerance
- Small luminous flux tolerances
- Colour temperatures 2700K, 3000K, 4000K, 5000K
- Optional push terminals for quick and simple wiring
- Dimmable
- Simple installation
- Long lifetime

APPLICATIONS

- Ideal for ceiling-mounted and wall-mounted luminaries
- Retrofits and fixtures
- Accent and Effect Lighting
- Professional downlights
- Shop lighting



CALCULATED PARAMETERS AT T_J = 25°C AND T_J = 65°C

	Input Current [mA]	Forward Voltage [V]	Power [W]	CCT [K]	Typ. CRI	Luminous Flux* [lm]	Module Efficacy* [lm/W]	Luminous Flux** [lm]	Module Efficacy** [lm/W]	Article Number
C0200	80	35	2,8	2700	83	383	137	370	132	L0-280024-827-C0200-K118
					93	349	125	337	120	L0-280024-927-C0200-K118
				3000	83	383	137	370	132	L0-280024-830-C0200-K118
					93	349	125	337	120	L0-280024-930-C0200-K118
				4000	83	414	148	400	143	L0-280024-840-C0200-K118
					93	377	135	364	130	L0-280024-940-C0200-K118
	125	36,2	4,5	2700	83	414	148	400	143	L0-280024-850-C0200-K118
					83	560	124	541	119	L0-280024-827-C0200-K118
				3000	93	509	113	492	109	L0-280024-927-C0200-K118
					83	560	124	541	119	L0-280024-830-C0200-K118
				4000	93	509	113	492	109	L0-280024-930-C0200-K118
					83	605	134	584	129	L0-280024-840-C0200-K118
	175	37,6	6,5	2700	93	550	122	532	117	L0-280024-940-C0200-K118
					83	605	134	584	129	L0-280024-850-C0200-K118
				3000	83	739	739	714	714	L0-280024-827-C0200-K118
					93	672	672	649	649	L0-280024-927-C0200-K118
				4000	83	739	739	714	714	L0-280024-830-C0200-K118
					93	672	672	649	649	L0-280024-930-C0200-K118
C0400	175	17,6	3,1	2700	83	798	122	771	118	L0-280024-840-C0200-K118
					93	726	111	701	107	L0-280024-940-C0200-K118
				3000	83	798	122	771	118	L0-280024-850-C0200-K118
					83	414	134	400	130	L0-280024-827-C0400-K118
				4000	93	377	122	364	118	L0-280024-927-C0400-K118
					83	414	134	400	130	L0-280024-830-C0400-K118
	250	18,1	4,5	2700	93	377	122	364	118	L0-280024-930-C0400-K118
					83	447	145	432	140	L0-280024-840-C0400-K118
				3000	93	407	132	393	128	L0-280024-940-C0400-K118
					83	447	145	432	140	L0-280024-850-C0400-K118
				4000	83	560	124	541	119	L0-280024-827-C0400-K118
					93	509	113	492	109	L0-280024-927-C0400-K118
	350	18,7	6,5	2700	83	560	124	541	119	L0-280024-830-C0400-K118
					93	509	113	492	109	L0-280024-930-C0400-K118
				3000	83	605	134	584	129	L0-280024-840-C0400-K118
					93	550	122	532	117	L0-280024-940-C0400-K118
				4000	83	605	134	584	129	L0-280024-850-C0400-K118
					83	739	113	714	109	L0-280024-827-C0400-K118
	350	18,7	6,5	2700	93	672	103	649	99	L0-280024-927-C0400-K118
					83	739	113	714	109	L0-280024-830-C0400-K118
				3000	93	672	103	649	99	L0-280024-930-C0400-K118
					83	798	122	771	118	L0-280024-840-C0400-K118
				4000	93	726	111	701	107	L0-280024-940-C0400-K118
					83	798	122	771	118	L0-280024-850-C0400-K118

* - Parameters were calculated for temperatures T_J= 25°C

** - Parameters were calculated for temperatures T_J= 65°C

Value of these parameters were calculated for default bin and with tolerances of 15%.

Please contact us before ordering for more information.

	Input Current [mA]	Forward Voltage [V]	Power [W]	CCT [K]	Typ. CRI	Luminous Flux* [lm]	Module Efficacy* [lm/W]	Luminous Flux** [lm]	Module Efficacy** [lm/W]	Article Number
C0600	250	11,7	2,9	2700	83	397	136	384	131	L0-280024-827-C0600-K118
					93	361	123	349	119	L0-280024-927-C0600-K118
				3000	83	397	136	384	131	L0-280024-830-C0600-K118
					93	361	123	349	119	L0-280024-930-C0600-K118
				4000	83	429	147	414	142	L0-280024-840-C0600-K118
					93	390	133	377	129	L0-280024-940-C0600-K118
	350	12	4,2	2700	83	429	147	414	142	L0-280024-850-C0600-K118
					93	390	133	377	129	L0-280024-950-C0600-K118
				3000	83	528	126	510	122	L0-280024-827-C0600-K118
					93	481	114	464	111	L0-280024-927-C0600-K118
				3000	83	528	126	510	122	L0-280024-830-C0600-K118
					93	481	114	464	111	L0-280024-930-C0600-K118
	500	12,4	6,2	4000	83	571	136	551	131	L0-280024-840-C0600-K118
					93	519	124	502	119	L0-280024-940-C0600-K118
				5000	83	571	136	551	131	L0-280024-850-C0600-K118
					93	519	124	502	119	L0-280024-950-C0600-K118
	500	12,4	6,2	2700	83	710	115	686	111	L0-280024-827-C0600-K118
					93	646	104	624	101	L0-280024-927-C0600-K118
C0800	350	8,8	3,1	2700	83	414	134	400	130	L0-280024-827-C1200-K118
					93	377	122	364	118	L0-280024-927-C1200-K118
				3000	83	414	134	400	130	L0-280024-830-C1200-K118
					93	377	122	364	118	L0-280024-930-C1200-K118
				4000	83	447	145	432	140	L0-280024-840-C1200-K118
					93	407	132	393	128	L0-280024-940-C1200-K118
	500	9,1	4,5	5000	83	447	145	432	140	L0-280024-850-C1200-K118
					93	407	132	393	128	L0-280024-950-C1200-K118
				2700	83	560	124	541	119	L0-280024-827-C1200-K118
					93	509	113	492	109	L0-280024-927-C1200-K118
				3000	83	560	124	541	119	L0-280024-830-C1200-K118
					93	509	113	492	109	L0-280024-930-C1200-K118
	700	9,4	6,5	4000	83	605	134	584	129	L0-280024-840-C1200-K118
					93	550	122	532	117	L0-280024-940-C1200-K118
				5000	83	605	134	584	129	L0-280024-850-C1200-K118
					93	550	122	532	117	L0-280024-950-C1200-K118
	700	9,4	6,5	2700	83	739	113	714	109	L0-280024-827-C1200-K118
					93	672	103	649	99	L0-280024-927-C1200-K118
				3000	83	739	113	714	109	L0-280024-830-C1200-K118
					93	672	103	649	99	L0-280024-930-C1200-K118
				4000	83	798	122	771	118	L0-280024-840-C1200-K118
					93	726	111	701	107	L0-280024-940-C1200-K118
	700	9,4	6,5	5000	83	798	122	771	118	L0-280024-850-C1200-K118
					93	726	111	701	107	L0-280024-950-C1200-K118

* - Parameters were calculated for temperatures $T_j = 25^{\circ}\text{C}$

** - Parameters were calculated for temperatures $T_j = 65^{\circ}\text{C}$

Value of these parameters were calculated for default bin and with tolerances of 15%.

Please contact us before ordering for more information.

	Input Current [mA]	Forward Voltage [V]	Power [W]	CCT [K]	Typ. CRI	Luminous Flux* [lm]	Module Efficacy* [lm/W]	Luminous Flux** [lm]	Module Efficacy** [lm/W]	Article Number
C1200	500	5,9	2,9	2700	83	397	136	384	131	L0-280024-827-C1200-K118
					93	361	123	349	119	L0-280024-927-C1200-K118
				3000	83	397	136	384	131	L0-280024-830-C1200-K118
					93	361	123	349	119	L0-280024-930-C1200-K118
				4000	83	429	147	414	142	L0-280024-840-C1200-K118
					93	390	133	377	129	L0-280024-940-C1200-K118
				5000	83	429	147	414	142	L0-280024-850-C1200-K118
					93	429	147	414	142	L0-280024-950-C1200-K118
	700	6	4,2	2700	83	528	126	510	122	L0-280024-827-C1200-K118
					93	481	114	464	111	L0-280024-927-C1200-K118
				3000	83	528	126	510	122	L0-280024-830-C1200-K118
					93	481	114	464	111	L0-280024-930-C1200-K118
				4000	83	571	136	551	131	L0-280024-840-C1200-K118
					93	519	124	502	119	L0-280024-940-C1200-K118
				5000	83	571	136	551	131	L0-280024-850-C1200-K118
					93	571	136	551	131	L0-280024-950-C1200-K118
	1050	6,2	6,5	2700	83	739	113	714	109	L0-280024-827-C1200-K118
					93	672	103	649	99	L0-280024-927-C1200-K118
				3000	83	739	113	714	109	L0-280024-830-C1200-K118
					93	672	103	649	99	L0-280024-930-C1200-K118
				4000	83	798	122	771	118	L0-280024-840-C1200-K118
					93	726	111	701	107	L0-280024-940-C1200-K118
				5000	83	798	122	771	118	L0-280024-850-C1200-K118
					93	798	122	771	118	L0-280024-950-C1200-K118

* - Parameters were calculated for temperatures $T_J = 25^{\circ}\text{C}$

** - Parameters were calculated for temperatures $T_J = 65^{\circ}\text{C}$


Value of these parameters were calculated for default bin and with tolerances of 15%.

Please contact us before ordering for more information.

Parameters shown in table above are default and for temperatures $T_J = 25^{\circ}\text{C}$ and $T_J = 65^{\circ}\text{C}$. Some of these parameters are temperature dependent and can be different during long time of operation. So it is impossible to order modules with the same parameters after some time. LED technology is developed fast and producers are creating new LEDs with better features very quick. If you need LED modules with different value of some parameters, we provide other LEDs with different colour temperature and features. It is possible to make modification of LED modules or create a new one. In such cases and for more information, please contact us before ordering. Please have all of this in mind when ordering LED modules.

MACADAM ELLIPSE

Producing LEDs with the same colour temperature is almost impossible. LEDs with similar colours are divided into bins. MacAdam Ellipses are used to describe differences in colour of LEDs with the same bin. When most people can't see very small differences in colours, these colours are in first step level of MacAdam Ellipse (1SDCM). If the differences are getting bigger, then number of step is increasing. Second zone of MacAdam ellipse (2SDCM) is twice bigger than first one and so on. Differences in colour for 3000K LEDs can be up to $\pm 30K$ in 1SDCM. If bin is in 4SDCM, then colour differences should be less than $\pm 100K$. LEDs with smaller number of SDCM are better. Most common LEDs are in 4th to 7th step level, in other words human eyes certainly can see colour differences in LEDs that are ostensibly the same colour. In most of our projects have been used LEDs in 3rd step level, so differences in colour aren't as big as fourth step level of MacAdam Ellipse.



PROTECTION MEASURES AGAINST DAMAGE

LED modules are delicate, even small mechanical stress may damage modules. Especially sensitive are LEDs. Such stresses should be avoided. If it is impossible, it should be reduced to minimum. Mechanical stresses such as pressure, bending, breaking, drilling, etc. may cause irreversible damage. Damaged LED modules aren't suitable for use.

Serious threat to LEDs is ESD. People generate very high electrostatic voltage. Such voltage decreases lifetime of LEDs and in worst case may destroy electronic components. Best way to avoid damage is use of electrostatic protection. Do not touch electronic components.

Additionally LED modules can be damaged by some chemical substances. Depends of elements the damage may be different. It is important not to use chemical substances like acids, organic acids, sulphur, alkalis, organic solvents, mineral oils, vegetable oils and synthetic oils, etc. We are not responsible for any loss, or damage resulting from improper use of modules! Guarantee become void in such cases.

Do not operate LED modules, when they aren't working properly. If modules are working incorrectly, turn off power supply. Damaged LED modules may cause electric shock or short circuit.


SAFETY

Most of LEDs generate high intensity light even when dimmed. If LED light has high intensity, it is classified as laser. These LEDs must have appropriate marking. Combination of LEDs or even weak LEDs with optics can be very dangerous, because optics can focus beam and looking into LEDs beam is unhealthy and may cause irreversible injury to eye's retina. Never look into the beam without protection glasses with appropriate filter.

Additionally LED light can change intensity almost immediately. If people are photosensitive, LED light may be a trigger to epileptic seizures and alter the perception, especially when light changes very fast.

CONNECTIONS


Connecting few LED modules allows to create complex lighting. Push terminals provide quick installation of the entire lighting system. The LED modules must be operated with power supply that is suitable for LEDs. When connecting a few LED modules use of appropriate power supply is important. Power supply should have sufficient maximum power to maintain all LED modules. Power supply must be connected properly. Wrong polarization can destroy modules in very short time. We are not responsible for any loss, or damage resulting from improper use of modules! Guarantee become void in such cases. Modules can be operated using a LED controller. It allows to use light effects, dimmer, etc. Thanks to dimmer it is possible to eliminate almost immediately change of light intensity. It is possible because LEDs are full controlled. Slower changes of light intensity are more safety for people with photosensitivity. We have got several different dimmers like touchable, RC, IR and Bluetooth in our offer. Most controllers have many light effects such as fire, thunderstorm, rainbow changes, strobe, etc. Some of these allow to create new effects, that are programmable via software.

WIRING DIAGRAM FOR LED CC MODULES WITH PARALLEL WIRING


Disadvantage of this solution are patchy distribution of light and different lifetime of LEDs. Especial when one or more LED modules are damage, because distribution of current in the system is patchy. Higher current increases temperature and decreases lifetime. If too many LED modules are connected in serial, the voltage value may not meet requirements of SELV. Non-SELV voltage need additional protection. We are not responsible for any loss, or damage resulting from improper use of modules! Guarantee become void in such cases. Above connection is examples and may be different from the actual.

COOLING

The modules are usually self-cooling but if temperature on T_c point exceeds 70°C , then a heat-sink is required. Temperature test point (T_c) for measurement should be localized in the middle of the board near LED's thermal pad. The temperature at the T_c point can be measured with thermocouple or simple temperature probe. Example of T_c point is shown on the photo below.



The lifetime of the module depends to operating temperature and used LEDs. If temperature at T_c will be lower than 65°C , the value of luminous flux shouldn't be less than 80% of its nominal value after 50.000h. If temperature is too high then lifetime can be significantly decreased or damage LEDs. Another disadvantage of high temperature is reduction of relative luminous intensity. LED modules produces heat. They must be provided with good air ventilation. Modules without air ventilation can overheat. Overheat can damage or destroy some elements or entire LED modules. We are not responsible for any loss, or damage resulting from improper use of modules! Guarantee become void in such cases.



Most common problem using new modules in old installation is differences in brightness of modules. This is result of luminous flux degradation over time of use. Degradation is normal effect and applies to all LEDs. This effect is different for each LEDs and can be only predicted by testing and estimation. It is complicate issue that mostly depends on temperature and current. Good solution to this problem is reduce of current in new modules, but degradation will be different for each modules. Above characteristic is examples for LEDs in temperature above 100°C and different from the actual.

STANDARDS AND DIRECTIVES

In the process of designing and manufacturing the following standards and directives were taken into account:

- 2014/35/EU – Low-voltage Directive: on the harmonisation of the laws of the Member States relating to the making available on the market of electrical equipment designed for use within certain voltage limits
- 2014/30/EU – EMC Directive: on the harmonisation of the laws of the Member States relating to electromagnetic compatibility
- 2011/65/EC – RoHS Directive: restriction of hazardous substances in electrical and electronic equipment
- EN 62031:2010/A1:2013-06 – Safety requirements for LED modules
- EN 60598-1:2015-04 – General requirements and tests for luminaires
- EN 60598-2-2:2012 – Luminaires - Part 2. Special requirements; Main section 2: Recessed luminaires
- EN 62471:2010 – Photo-biological safety of lamps and lamps systems
- EN 61347-1:2015-09 – General and safety requirements
- EN 61347-2-13:2015-04 – Special requirements for DC and AC powered electronic operating equipment for LED modules
- EU Regulation No: 874/2012 – Energy labelling of electrical lamps and luminaries

CONTACT

CEZOS

81-534 Gdynia POLAND,

Olgiarda 88/b

tel. +48 58 664 88 61

cezos@cezos.com

www.cezos.com

Subject to technical changes and errors.